Faculty of Physics and Astronomy
Rupertus Carola University of Heidelberg

Diploma Thesis

in Physics

submitted by

Jan Becker

born in Hamburg (Germany)

2000

The Data Aquisition and Control System for a Fast Trigger at H1

This diploma thesis has been carried out by Jan Becker at the

Institute of Physics

under the supervision of

Prof. Dr. Franz Eisele

The Data Aquisition and Control System for a Fast Trigger at H1

The HERA (**H**adron-**E**lektron-**R**ing-**A**nlage) particle collider at DESY in Hamburg (Germany) is operating since May 1992. An upgrade for HERA is planned for 2000/2001 to gain higher luminosity. A bigger number of background events is therefore also expected. A new fast trigger called CIP2000 trigger is developed to examine and suppress the background events. The trigger system uses the pad information of five cylindrical multiwire chambers to calculate a histogramm of track origins along the beam axis. From the structure of this histogram background events can be identified. The aim of this diploma thesis is to develop and test the control system and the readout system for the new trigger. The communication between the different CPUs (pVIC) and the communication between the CPUs and the newly designed trigger cards (VME) are tested in a test system. Different data reduction algorithms to reduce the size of the read out events are simulated. The connection and communication of the STC (**S**ubsystem **T**rigger **C**ontrol) system and the CIP2000 trigger system is defined and some parts of the communication are tested. The control system for the whole CIP2000 trigger system is specified.

Das Datennahme- und Kontrollsystem für einen schnellen Trigger bei H1

Der HERA (**H**adron-**E**lektron-**R**ing-**A**nlage) Elektron-Proton-Speicherring am DESY in Hamburg (Deutschland) ist seit Mai 1992 in Betrieb. Eine Erhöhung der Luminosität von HERA ist für die Jahre 2000/2001 geplant. Deshalb wird auch eine größere Anzahl von Untergrundereignissen erwartet. Ein neuer schneller Trigger (CIP2000 Trigger) wurde entwickelt, um die Untergrundereignisse zu untersuchen und zu unterdrücken. Das Triggersystem benutzt die Kammerinformationen von fünf zylindrischen Kammern, um ein Histogramm der rekonstruierten Spurursprünge entlang der Strahlachse zu berechnen. An der Struktur dieses Histogramms können Untergrundereignisse erkannt werden. Das Ziel dieser Diplomarbeit ist die Entwicklung und der Test eines Kontroll- und Datennahmesystems für den neuen Trigger. Die Kommunikation der verschiedenen CPUs (pVIC) und die Kommunikation zwischen den CPUs und den neu entwickelten Triggerkarten (VME) wurde an Hand eines Testsystems untersucht. Verschiedene Datenreduktionsalgorithmen wurden simuliert, um die ausgelesene Datenmenge zu verkleinern. Die Verbindung des STC-Systems (**S**ubsystem **T**rigger **C**ontrol) mit dem CIP2000 Triggersystem wurde definiert und Teile dieser Verbindung getestet. Ein Kontrollsystem für das gesamte CIP2000 Triggersystem wurde entwickelt.

Contents

List of Figures

List of Tables

Chapter 1

Introduction

The HERA (**H**adron-**E**lektron-**R**ing-**A**nlage) particle collider at DESY in Hamburg (Germany) is operating since May 1992. An upgrade for HERA is planned for 2000/2001. In the upgrade the size of the focus of the beams is reduced leading to a higher luminosity. The detectors have to be adapted to the new situation. A bigger number of background events is expected. A new fast trigger is developed to examine and suppress the background events.
The new trigger system is called CIP2000 trigger system. The trigger system uses the pad information of five cylindrical chambers to find and count tracks originating from the beam axis. The number of tracks originating from different parts of the beam axis are summed up to a z-vertex histogram. The structure of the z-vertex histogram makes it possible to detect background events. The trigger system uses FPGAs (**F**ield **P**rogrammable **G**ate **A**rray) mounted on trigger cards to implement the trigger algorithm. The chamber data is stored in pipelines situated in the FPGAs. CPUs read out the data via a VME bus and a pVIC connection.
The aim of this diploma thesis is to develop the control system and the readout system for the new trigger. The communication of the different CPUs and the new designed trigger cards is tested in a test system. The pVIC bus between the different CPUs is examined. Different data reduction algorithms to reduce the size of the events read out from the pipelines are simulated. The communication of the different parts of the whole CIP2000 trigger system is designed. The connection and communication of the STC (**S**ubsystem **T**rigger **C**ontrol) system and the CIP2000 trigger system is specified and some parts of the communication are tested.

- **Chapter 2** gives an introduction to the HERA particle collider, the H1 detector and the upgrade for HERA 2000.

- **Chapter 3** gives an overview of the CIP2000 trigger system and the hardware components used in the system.

- **Chapter 4** explains the structure of the trigger control system and the system to control the whole CIP2000 system.

- **Chapter 5** gives an overview of the planned readout system of the CIP2000 trigger and its hardware components.
- **Chapter 6** gives an overview of tests made with the readout test system.
- **Chapter 7** shows the results of simulations of the data reduction on the raw data of the CIP2000 trigger readout system.

Chapter 2

HERA and the H1 detector

2.1 The HERA machine

Two independent machines reside in the 6.3 km long tunnel some 15 m below the surface. One is an electron (alternatively positron) storage ring, which accelerates the particles from an initial 14 GeV to 30 GeV. The proton machine starts with initial 40 GeV accelerating the protons to 920 GeV before a collision with the electrons or a target is forced. The energy of the proton beam is limited by the strength of the magnets needed to bend the beam on its orbit. The HERA proton ring consists of superconducting magnets which produce a field of 4.6 T. Figure 2.1 gives an overview of HERA and its injector chains. The particles are packed into a maximum of 210 bunches, with a bunch crossing distance of only 96 ns. Not all of the bunches are filled with particles. The bunch crossings with no interactions are used to determine the background situation. The currents of the beams have been successfully increased in the last years. At the moment four experiments use the HERA storage rings. H1 and ZEUS are built around two interaction regions of the storage rings. The HERMES detector records the scattering of the polarized electron



Figure 2.1: *The HERA storage ring with its pre-accelerators PETRA, DESY and Linacs*